

Signal Booster Installation Guide

Dual-Band Channelized 800 / 1900 MHz

In-Building Wireless
Smart Technology II™
Signal Booster



Contents:

Antenna Options & Accessories	1
Quick Install Overview	2
Installation Diagram	3
Before Getting Started	4
Outside Antenna Installation	5
Finding the Strongest Signal	7
Installing the Inside Antenna	8
Installing a Wilson Electronics Signal Booster	9
Powering up a Wilson Electronics Signal Booster	10
Adjusting Channel & Gain	11
Understanding the Signal Booster Lights & LCD Screen	13
Warnings and Recommendations	16
Guarantee & Warranty	18
Specifications	Back Cover

Appearance of device and accessories may vary.

Note: This manual contains important safety and operating information. Please read and follow the instructions in this manual. Failure to do so could be hazardous and result in damage to your Signal Booster.

Installation Instructions for the Following Wilson Electronic Signal Booster:

Dual-Band Channelized 800 / 1900 MHz

In-Building Wireless Smart Technology II™ Signal Booster

Model #277280 FCC: PWO277280 IC: 4726A-277280

The term "IC" before the radio certification number only signifies that Industry Canada technical specifications were met.

How it Works

Wilson Electronics Signal Boosters are bi-directional devices that deliver service levels consistent with what would be expected in areas of high cell network coverage. They amplify a weak or shadowed signal in mobile, M2M, marine and in-building applications. When using a Wilson Electronics Signal Booster in conjunction with Wilson Electronics antennas, the Outside Antenna will collect the cell tower signal and send it through the cable to the Signal Booster. The signal is then amplified and re-transmitted through the Inside Antenna into the room. Cell phones and cellular data cards in that area then communicate with the improved signal. When a cell phone or cellular device transmits, the signal is received by the Inside Antenna, amplified by the Signal Booster and transmitted back to the cell tower through the Outside Antenna.

Inside this Package

Note: Kits may contain different accessories



**AC/DC
Power Supply
(#859995)**



**Signal
Booster**

Outdoor Antenna Options

1. Wide Band Directional Antenna 700 MHz - 2700 MHz (304411)
2. Pole Mount Wide Band Panel Antenna (304453)

Indoor Antenna Options & Accessories


- A. Wide-Band Panel Antenna 700-2700 MHz (multiple mounting options available)
 - B. 50 Ohm Lightning Surge Protector N Connector (859902)
- Splitter options on page 9



1



2



A

B

Appearance of device and accessories may vary.

To purchase, call Wilson Electronics Sales Department at: 800-204-4104

We recommend using directional antennas with this Signal Booster.

Contact Wilson Electronics Technical Support Team with any questions at 866-294-1660 or email: tech@wilsonelectronics.com. Mon.- Fri. Hours: 7 am to 6 pm MST.


Quick Install Overview

See Installation Diagram on page 3 & 4. Contact Wilson Electronics Technical Support Team with any questions at 866-294-1660.

1. Select a location to install the Signal Booster that is away from excessive heat, direct sunlight, moisture and has proper ventilation. Do not place the Signal Booster in an air-tight enclosure.
2. Select a location on the roof of the building to install the Outside Antenna. Use a cell phone in test mode to find the strongest signal from the cell tower. Refer to page 5. Visit www.WilsonElectronics.com to find the test mode function for your particular cell phone.
3. Run the Outside Antenna cable to the Signal Booster and attach it to the connector labeled "Outside Antenna" on the Signal Booster. Run the Inside Antenna cable to the Signal Booster and attach it to the connector labeled "Inside Antenna" on the Signal Booster. Refer to page 8 for more information on running cable. Lightning Surge Protection is recommended for all in-building installations refer to page 6.
4. Select a location for the Inside Antenna, preferably in the center of where the signal needs to be amplified. A minimum separation distance of **20 vertical feet (within the null zone) or 50 horizontal feet** is necessary for proper operation. If the inside coverage is not sufficient you may need as much as **75 feet of horizontal** separation (refer to installation diagram on pages 3 & 4).
5. Before powering up the Signal Booster, verify that both the Outside Antenna and the Inside Antenna are connected and check that all connections are tight. Refer to page 9. **Note: Be careful when plugging the connectors in so as not to bend the center pins on the connectors.**
6. Press yellow "CH Select" button to desired setting. Your channel will show on the LCD screen. Refer to pages 10 & 11.
7. The Signal Booster has been packaged with the gain control knobs adjusted to the highest gain position. If lights are not green, please refer to pages 13 & 14.


⚠ Warning: Connecting the Signal Booster directly to a cell phone with use of an adapter will damage the cell phone and/or the Signal Booster.

IMPORTANT NOTICE



- It is very important to power your Signal Booster using a surge protected AC Power Strip with at least a **1000 Joule rating**.
- Failure to do this will void your warranty in the event of a power surge or lightning strike.

Installation Diagram



Inside Antenna

Preferred Method: Place the Inside Antenna in the ceiling facing down for the best coverage.


Note: The Inside Antenna may be mounted on the wall directly under the Outside Antenna, in the null zone, if 20 feet of vertical separation can be maintained.

Null Zone: The area under the Outside Antenna, where the Outside Antenna radiates the least.

Note: A Lightning Surge Protector is recommended for all building installations (sold separately). Make sure the protector is installed in line between the Outside Antenna and the Signal Booster.

Before Getting Started

This guide will help you properly install your Wilson Electronics Signal Booster. **It is important to read through all of the installation steps for your particular application prior to installing any equipment.** Read through the instructions, visualize where all the equipment will need to be installed and do a soft installation before mounting any equipment. Contact Wilson Electronics Technical Support with any questions at: 866-294-1660.



Reasons for Weak Cellular Signals

Anyone who uses a cell phone or cellular data card knows the frustration of not being able to connect to or maintain a strong cellular signal. When this occurs, it is generally due to one of two reasons:

1. Location of the Nearest Cell Tower – Cell towers are situated to provide broad coverage; however, there are many areas in which signal strength may be reduced by topographic features or by local government restrictions on the height or placement of the towers themselves. Rural areas generally have fewer cell towers than urban regions.
2. Natural and Man-Made Obstructions – Signal strength can also be negatively affected by trees, hills, buildings, weather, and other obstructions. You may be relatively close to a cell tower but still unable to make a call. This often occurs in homes, offices and other buildings in which stucco, concrete or metal walls may block the signal.

The Signal Booster works with two antennas. The Inside Antenna communicates with your cell phone and the Outside Antenna communicates with the cell tower. The Outside Antenna receives the cell tower signal and sends it through the cable to the Signal Booster, where it is amplified and transmitted through the Inside Antenna into the room. When the Inside Antenna picks up a signal from your cellular device, the Signal Booster amplifies that signal and transmits it through the cable, then through the Outside Antenna and back to the cell tower.

Note: *The Signal Booster will only operate if there is an adequate signal to amplify.*



Outside Antenna Installation


The antenna should be mounted as shown in the illustration above. The mounting bracket, included with antenna, is adjustable and will accommodate pipe diameters from 1.25" to 2" (pipe sold separately #901117). Mount the antenna so that there is at least 3 feet of clearance in all directions around it. Position the antenna so that it has an unobstructed line of sight to the cell tower's strongest signal. Make sure

the antenna is not pointing across your own roof or at the Inside Antenna as this will cause the oscillation protection circuitry to shut down the Signal Booster.

⚠ Warning: Lightning protection is recommended for all installations (#859902-50 Ohm shown below). Take extreme care to ensure that neither you nor the antenna comes near any electric power lines.

Installing Lightning Protection (sold separately)

Install the Lightning Surge Protector (LSP) close to the Signal Booster. Attach the cable from the Outside Antenna to the surge protector, using a short length of low loss cable; attach one end to the LSP and the other to the Outside Antenna connector on the Signal Booster. Ensure the LSP is properly grounded (ground wire not included). LSP sold separately, go to www.WilsonElectronics.com or call 800-204-4104 to order.




Selecting a Direction for the Outside Antenna

Before selecting a location on the roof of the building to install the Outside Antenna, see page 7 for additional instructions. Use a cell phone in test mode to find the strongest signal from the cell tower (refer to page 5 for more information). To get the strongest signal possible, it is very important to set up your Outside Antenna properly. The Inside and the Outside Antenna must be mounted in such a way that they are able to pick up the best possible cell signal on the outside of the building and provide the best possible signal on the inside of the building. Mount the Outside Antenna as high as possible facing the cell tower in an area with the best possible signal coverage.


Note: Never point the front of a directional antenna toward the Inside Antenna. See Figures 1 & 2 on page 10.

Finding the Strongest Signal

When installing your Signal Booster's Outside Antenna, aiming it towards the best signal source from your service provider is important. The best way of getting the strongest signal is to have one person on the roof to rotate the Outside Antenna, which is connected to the Signal Booster. Turn the Outside Antenna about 45 degrees at a time, while the second person is watching the signal strength on the phone inside the building. This allows you to read the signal strength from the cell tower. It is preferable to have the phone in the test mode so the actual signal strength can be read, as bars are not the most accurate. Go to www.WilsonElectronics.com for help in finding the test mode for your phone. Always make sure the person inside the building gives the signal time to arrive and register on the phone (between 10-30 seconds for phone to reset to the signal reading).



Signal readings usually appear as a negative number (for example, -86). The closer you get to zero the stronger the signal. (See graph below).



Mounting Tips for Running Outside Antenna Cable


If you are mounting the Outside Antenna on the roof of your building, we have found that it is easiest to run your cable underneath the down side of your roof's flashing. If you have satellite TV service installed you may be able to follow the same route as the satellite TV cables that are already running from outside of your building to the inside.

After routing the cable, we recommend sealing any areas where the cable passes into the building with cable bushings, silicone or a silicone-type sealant to keep your installation from leaking. If you are mounting the Outside Antenna to the outside wall of your home or building, the simplest way is to run the cable on the outside of the wall and attach it to the exterior of your home or office. Then drill a hole through the wall where you want the cable to appear on the inside of the building. Before drilling, make sure that there are no electrical outlets, sewer or water pipes, or electrical wiring in the wall that you are about to drill through as this could potentially harm you or damage the building.

After drilling the required hole, run the cable through and seal it with cable bushings or a silicone-type sealant to enclose the hole that you have created. In some instances, it may be possible to run the cable up into the fascia of the attic overhang. In this circumstance, the cable will be accessible in the attic for further routing.

Installing the Inside Antenna (Instructions are for optional Panel Antenna)

Select a location for the Inside Antenna, preferably in the center of where the signal needs to be amplified. A minimum separation distance of **20 vertical feet (within the null zone) or 50 horizontal feet** is necessary for proper operation. If the inside coverage is not sufficient you may need as much as **75 feet of horizontal** separation. Refer to installation diagram on pages 3 & 4.



In some cases, multiple Inside Antennas may be required, for instance if you have multiple rooms with poor signal. A signal may be split by using a splitter (sold separately). If using more than one Inside Antenna, a separation up to 75 **horizontal** feet may be necessary between Inside Antennas. Refer to the configuration on pages 3 & 4.



Optional Wide Band
Inside Antenna
(sold separately)

Multiple mounting
options available

Splitter Options:



2-way
(859957)

3-way
(859980)

4-way
(859981)

Installing a Wilson Electronics Signal Booster

Select a location to install the Signal Booster that is away from excessive heat, direct sunlight, moisture and that has proper ventilation. Do not place the Signal Booster in an air-tight enclosure. Recommended installation locations for in-building Signal Boosters are near a power outlet and in a closet or on a shelf.

Note: *It is important to have adequate air ventilation. Maintain at least 6 inches of clearance from surrounding objects. Be careful when plugging the connector in so as not to damage the center pins on the connectors.*

Run the Outside Antenna cable to the Signal Booster and attach it to the connector labeled “Outside Antenna” on the Signal Booster. Run the Inside Antenna cable to the Signal Booster and attach it to the connector labeled “Inside Antenna” on the Signal Booster.

Note: *For distances of 20 feet or more, use Wilson low loss cable.*

Note: *It is very important to power your Signal Booster using a surge protected AC Power Strip with at least a **1000 Joule rating**. Failure to do this will void your warranty in the event of a power surge or lightning strike.*

Warning: An Inside Antenna must have a separation distance from all persons that is at least 8 inches for the Panel Antenna.




Figure 1




Figure 2


Powering up a Wilson Electronics Signal Booster

1. Never point the front of a directional Outside Antenna toward the Inside Antenna. See Figures 1 & 2 above.
2. Ensure that both the Outside Antenna cable and the Inside Antenna cable are connected to the Signal Booster **and the connections are tight** before powering up the Signal Booster.
3. Plug the power supply into the Signal Booster input marked “6V DC” (carefully, to avoid damaging the center pin) and then into a surge protected AC Power Strip.
4. If the Signal Booster does not have green lights, please refer to pages 13 & 14.
5. Using multiple Signal Boosters in one installation could cause interference to the cell tower.
6. Contact Wilson Electronics Technical Support Team with any questions at 866-294-1660 or email tech@wilsonelectronics.com. Technical Support hours are Mon.- Fri. 7 am to 6 pm MST.

Adjusting Channel and Gain

Note: For a list of channel options see tables on page 15.


1. If you know your desired channel setting, press or hold down the CH Select button until the desired channel is displayed on the LCD screen. See pages 13-14 for further instructions about the LCD screen display numbers.
2. The LCD screen should look similar to Figure 3 for 800 MHz and Figure 4 for 1900 MHz. If it does not appear similar to the figure below (refer to the troubleshooting section on pages 13 & 14).
3. Push the 800 MHz “CH Select” or 1900 MHz “CH Select” button to change channels. This button also toggles between the 800 MHz and 1900 MHz LCD screens.
4. If you do not know your channel setting:
Option 1: Watch the signal strength on your phone inside the building. (To put your phone in test mode visit www.WilsonElectronics.com or contact Wilson Electronics Technical Support Team at 866-294-1660.) This allows you to read the signal strength from the cell tower. Press the yellow “CH Select” button until you have the best signal. Refer to page 7 on how to read the signal strength from the cell tower.
Option 2: You may also contact your wireless service provider for optimal channel setting information for your area.
5. When the 800 MHz LCD screen is selected, the channel is indicated at the bottom center of the LCD screen (refer to Figure 3 below).




Example shown – numbers on LCD screen will vary.

6. Pressing the 800 MHz “CH Select” button steps between channels listed in Table 1 on page 15.

- When the 1900 MHz LCD screen is selected, the pass bandwidth is indicated at the bottom center of the LCD screen and the Uplink (UL) center frequency is at the top of the screen (refer to Figure 4). The corresponding Downlink (DL) frequency automatically adjusts and is always 80 MHz higher than the UL frequency shown. For common settings please see Table 2 on page 15.



- Pressing the 1900 MHz “CH Select” button toggles between 5 and 15 MHz pass bandwidth and increases the UL center frequency in 2.5 MHz increments.
- The UL and DL gains are displayed on the LCD screen similar to Figures 3 and 4. UL gain is shown on the left, and DL gain is shown on the right.
- If a red light or “OVERLOAD” is displayed on LCD screen, turn the 800 or 1900 MHz knob as shown in Figure 5.



Understanding the Signal Booster Lights, LCD Screen and Troubleshooting

During installation mode the Signal Booster is resetting itself very quickly to aid the installer. The Signal Booster is equipped with two indicator lights shown in Figure 8 on page 14. For the first 15 minutes that the booster is plugged in, it is programmed for a test and alignment period. During this time, the light and the LCD will do one of the following 4 things:

Note: *If after the initial 15 minutes you are not done with the installation, the Signal Booster can be reset and enter installation mode again by disconnecting and reconnecting the power supply from the booster.*

1. BLINKING GREEN

If the Signal Booster is blinking green, the Signal Booster is operating properly. If you are happy with the coverage area in your building, then you are done. Blinking will stop after the 15 minute installation period.

2. LCD SCREEN OVERLOAD

If the LCD screen displays “OVERLOAD,” (see Figure 6) the Signal Booster has automatically reduced gain to protect a nearby cell tower. First turn the appropriate gain control knob until the “OVERLOAD” is replaced by the normal LCD screen (see Figure 7). The booster is now working with reduced gain. If the gain is not adequate for good coverage, you will need to turn the gain to maximum and then turn the Outside Antenna away from the cell tower until the “OVERLOAD” is replaced by the normal LCD screen. If the booster will not respond, turn the gain down 5 dB and move the Outside Antenna position until the “OVERLOAD” is replaced by the normal LCD screen.

Figure 6





Figure 7



3. SOLID RED



If the light on the Signal Booster is solid red, this indicates that the Signal Booster has shut down on that frequency

to prevent an oscillation (feedback). First, make sure that all the connections are tight. Then reduce the gain of the booster in small increments by rotating the appropriate gain control knob counter clockwise, waiting 5 seconds between each adjustment for the booster to reset. Continue this adjustment until the light turns blinking or solid green. When you are turning down the gain, you are reducing the coverage

area. If the amount of coverage area is sufficient for your needs and the light is green, the installation is complete. If the coverage area is not large enough, it is necessary to increase the separation distance of the Inside and Outside Antennas by moving them horizontally or vertically farther apart. Then increase the

gain until the red light comes on, and then slightly decrease the gain until the green or blinking green light appears. If after separating the antennas your coverage area is still too small, contact Wilson Electronics Technical Support Team for assistance: 866-294-1660. If your installation takes longer than 15 minutes, it is possible to re-enter the installation mode by disconnecting and reconnecting the power supply from the Signal Booster.

Figure 8



4. SOLID GREEN

The indicator light on the Signal Booster will be a solid green after the first 15 minute installation period, if the unit is powered up and working properly.

Table 1**800 MHz Channel Selections**

U.S. Cellular Band				
Channel Options	Uplink		Downlink	
	Lower Band MHz	Upper Band MHz	Lower Band MHz	Upper Band MHz
AA'	824-835	845-846.5	869-880	890-891.5
BB'	835-845	846.5-849	880-890	891.5-894
B	835-845	-	880-890	-

Table 2**Common 1900 MHz Channel Selections**






U.S. PCS Band			
User can select any 5 or 15MHz band within the U.S. PCS Band in 2.5MHz steps. Some common channel blocks are listed below.			
Common Channel Blocks*	UL Frequency Setting (MHz)	Bandwidth Setting (MHz)	Corresponding DL Center Frequency (MHz)
A	1857.5	15	1937.5
B	1877.5	15	1957.5
C	1902.5	15	1982.5
C1	1907.5	5	1987.5
C2	1897.5	5	1977.5
C4	1902.5	5	1982.5
C5	1907.5	5	1987.5
D	1867.5	5	1947.5
E	1887.5	5	1967.5
F	1892.5	5	1972.5

*Not all channel options are listed

Table 3**Channel Filter Characteristics**

Pass Bandwidth (BW) MHz	-3dB BW MHz	-40dB BW MHz	-45 dB BW MHz
1.5	2.20	4.29	4.45
2.5	2.75	4.75	4.85
5	5.08	7.7	7.85
10	10.1	12.9	13.2
15	15.05	18.35	18.6

Warnings and Recommendations

-  Warning: The Outside Antenna must always be located so the back or side points to the Inside Antenna. Never point the front of the Outside Antenna toward the Inside Antenna – this is to prevent oscillation.
-  Warning: Connecting the Signal Booster directly to the cell phone with use of an adapter will damage the cell phone and/or Signal Booster.
-  Warning: Use only the correct Wilson Electronics power supply. Use of a non-Wilson Electronics product may damage your equipment.
-  Warning: **RF Safety:** FCC regulations require that any fixed Outside Antenna used with this Signal Booster may not have gain (less cable loss) that exceeds 15 dBi gain and must be located at least 21 inches from all people. Inside Antennas must not exceed 12.1 dBi gain (less cable loss) and must be located at least 8 inches from all people.
-  Warning: Verify that both the Outside Antenna and the Inside Antenna are connected to the Signal Booster before powering up the Signal Booster.

Recommendation: Omni Directional Antennas are not recommended with this Signal Booster.

Recommendation: Lightning Surge Protection is recommended for all in-building installations.

This device complies with Part 15 of FCC rules. Operation is subject to two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. Changes or modifications not expressly approved by Wilson Electronics could void the authority to operate this equipment.

30-Day Money-Back Guarantee

All Wilson Electronics products are protected by Wilson Electronics 30-day money-back guarantee. If for any reason the performance of any product is not acceptable, simply return the product directly to the reseller with a dated proof of purchase.

1-Year Warranty

Wilson Electronics Signal Boosters are warranted for one (1) year against defects in workmanship and/or materials. Warranty cases may be resolved by returning the product directly to the reseller with a dated proof of purchase.

Signal Boosters may also be returned directly to the manufacturer at the consumer's expense, with a dated proof of purchase and a Returned Material Authorization (RMA) number supplied by Wilson Electronics. Wilson Electronics shall, at its option, either repair or replace the product. Wilson Electronics will pay for delivery of the repaired or replaced product back to the original consumer if located within the continental U.S.

This warranty does not apply to any Signal Booster determined by Wilson Electronics to have been subjected to misuse, abuse, neglect, or mishandling that alters or damages physical or electronic properties.

Failure to use a surge protected AC Power Strip with at least a 1000 Joule rating will void your warranty.

RMA numbers may be obtained by contacting Technical Support at 866-294-1660.

Disclaimer : The information provided by Wilson Electronics, Inc. is believed to be complete and accurate. However, no responsibility is assumed by Wilson Electronics, Inc. for any business or personal losses arising from its use, or for any infringements of patents or other rights of third parties that may result from its use.

Copyright © 2012 Wilson Electronics, Inc. All rights reserved.

U.S. Patent Nos. – 7,221,967; 7,729,669; 7,486,929; 7,409,186; 7,783,318



About Wilson Electronics

Wilson Electronics, Inc. has been a leader in the wireless communications industry for over 40 years. The company designs and manufactures Signal Boosters, antennas and related components that significantly improve cellular telephone signal reception and transmission in a wide variety of applications, both mobile (marine, RV, vehicles) and in-building (home, office, M2M).

With extensive experience in antenna and Signal Booster research and design, the company's engineering team uses a state-of-the-art testing laboratory, including an anechoic chamber and network analyzers, to fine-tune antenna designs and performance. For its Signal Boosters, Wilson Electronics uses a double electrically shielded RF enclosure and cell tower simulators for compliance testing.

Wilson Electronics Signal Boosters feature patented Smart Technology II™ that enables them to automatically adjust their power based on cell tower requirements. By detecting and preventing oscillation (feedback), signal overload and interference with other users, these Smart Technology II™ Signal Boosters improve network cell phone areas without compromising carrier systems.

All products are engineered and assembled in the company's 55,000-square-foot headquarters in St. George, Utah. Wilson Electronics has product dealers in all 50 states as well as in countries around the world.

Signal Booster Specifications

		Dual-Band Channelized 800 / 1900 MHz	
Model Number		277280	
Antenna connectors		N-Female	
Antenna Impedance		50 Ohms	
Dimensions		8.875 x 6.0 x 1.5 inch (22.5 x 15.2 x 3.8 cm)	
Weight		2.8 lbs (1.270 kg)	
Frequency		824-894 / 1850-1990 MHz	
*Channels Passband Gain (nominal)		Uplink Typical / Maximum	Downlink Typical / Maximum
	800 MHz	70 dB / 77 dB	77 dB / 85 dB
	1900 MHz	75 dB / 83 dB	71 dB / 78 dB
*20 dB Bandwidth (nominal)		Uplink Typical / Maximum	Downlink Typical / Maximum
	800 MHz	26 MHz / 29 MHz	26 MHz / 29 MHz
	1900 MHz	61 MHz / 67 MHz	61 MHz / 67 MHz
*Power output for single cell phone (uplink) dBm		800 MHz	1900 MHz
	CDMA	27.6	27.2
	EDGE	27.5	24.8
	GSM	27.6	25.1
	WCDMA	26.9	26.4
	LTE	26.8	26.5
*Power output for single cell phone (downlink) dBm		800 MHz	1900 MHz
	CDMA	19.3	21.9
	EDGE	18.7	21.2
	GSM	21.8	21.7
	WCDMA	18.5	20.9
	LTE	21.5	22.3
*Power output for multiple transmitted signals (uplink) dBm		Maximum Power	
The maximum power is reduced by the number of signals:	Number of signals	800 MHz	1900 MHz
	2	24.6	25.4
	3	21.1	21.8
	4	18.6	19.3
	5	16.7	17.4
	6	15.1	15.8
*Power output for multiple transmitted signals (downlink) dBm		Maximum Power	
The maximum power is reduced by the number of signals:	Number of signals	800 MHz	1900 MHz
	2	23.2	20.6
	3	19.6	17.1
	4	17.1	14.6
	5	15.2	12.7
	6	13.6	11.1
Noise Figure (typical downlink/uplink)		3.5 dB nominal	
Isolation		> 90 dB	
Power Requirements		110-240 V AC, 50-60 Hz, 20 W	

Notes: 1. Nominal gain is the maximum gain at any frequency in the passband.

2. Nominal bandwidth is the difference between two frequencies that are adjacent to the passband where the amplification is 20 dB lower than the passband amplification. One of the frequencies is lower than the passband and the other is higher.

3. The Manufacturer's rated output power of this equipment is for single carrier operation. For situations when multiple carrier signals are present, the rating would have to be reduced by 3.5 dB, especially where the output signal is re-radiated and can cause interference to adjacent band users. This power reduction is to be by means of input power or gain reduction and not by an attenuator at the output of the device.

4. The maximum power for 2 or more simultaneous signals will be reduced by 6 dB every time the number of signals is doubled.



3301 East Deseret Drive, St. George, UT 84790
 For additional Technical Support visit www.WilsonElectronics.com
 or email at: tech@wilsonelectronics.com
 Phone: 866-294-1660 Local: 435-673-5021 Fax: 435-656-2432
www.twitter.com/WilsonCellular www.facebook.com/WilsonCellular